

AL802-WAL NAC Power Extender (8 A)

www.boschsecurity.com



BOSCH

Invented for life



- ▶ Two (2) Class A or four (4) Class B outputs
- ▶ Input to Output Follower mode maintains synchronization of NAC devices
- ▶ AC Fail, Low Battery, and Battery Presence supervision
- ▶ LEDs indicate prior fault on one or more signaling circuit outputs
- ▶ One auxiliary power output (1 A supply current) with battery backup

The AL802-WAL NAC Power Extender is a cost-effective 8 A remote power supply and battery charger that can be connected to any 12 VDC or 24 VDC fire alarm control panel (FACP). Its primary application is to provide notification appliance circuit (NAC) expansion support that meets Americans with Disabilities Act (ADA) requirements. It can also be used to provide auxiliary power to support system accessories.

Functions

Battery Backup

There is a built-in charger for sealed lead-acid or gel-type batteries. The enclosure has room for two 12 VDC, 12 Ah batteries. If AC fails, there is automatic switchover (with zero voltage drop on switchover) to standby battery.

Inputs

Power input is 115 VAC, 60 Hz, 1.45 A. There are two normally-closed (NC) dry contact trigger inputs. The unit is equipped for two Class A or two Class B FACP inputs.

NAC Loop Supervision

In non-alarm conditions, independent loop supervision for Class A and/or Class B FACP NACs is provided. In the event of a loop trouble, the FACP is notified by the steered input (input 1 or input 2). In addition, there are common trouble output terminals (NC, C, NO) that are used to indicate general loop or system trouble. A common trouble input is provided for optional normally-closed (NC) devices to report trouble to the FACP. Two FACP signaling outputs can be employed and directed to control supervision and power delivery to any combination of the four outputs. The unit also has Loop Output trouble memory indication to help identify troublesome sporadic problems.

Outputs

The AL802-WAL delivers electronically regulated and filtered 12 V or 24 V power to Class B or Class A NAC loop circuits. Additionally, a separate 1.0 A auxiliary output for four-wire smoke detectors is available. The 8 A maximum alarm current can be divided among the four outputs for powering NAC devices. Each output is rated at 2.5 A maximum. The outputs are Class 2 rated power limited outputs with auto reset thermal and short-circuit protection.

Output Programming

Each output can be independently programmed for Steady, Temporal Code 3, or Strobe synchronization. All outputs can be programmed for Input to Output Follower mode.

Paralleling Outputs

An individual output of 4 A can be obtained by paralleling two outputs.

Horn and Strobe Synchronization

The two-wire synchronization mode works with the Gentex Commander GOS Sync Mode 3, 4 and ST/HS series, the System Sensor SpectrAlert series of horns, strobes, and horn strobe combinations, and Cooper Wheelock horns, strobes, and horn strobe combinations to provide a means of synchronizing the temporal-coded horns, synchronizing the flash timing of the strobe, and silencing the horns of the horn strobe combination over a two-wire circuit while leaving the strobes active.



Notice

The AL802-WAL will synchronize only the horns, horn strobes and strobes that contain synchronization capability.

Certifications and approvals

Altronix Corp. holds these Listings and Approvals:

NFPA Complies with NFPA 72

Region	Certification	
USA	UL	UOXX: Control Unit Accessories, System (UL864)
	FM	AL802-WAL
	CSFM	see our website

Parts included

Quant.	Component
1	NAC power extender
1	AL802 logic board (AL800LGK9E)
1	Enclosure (red)
1	Cam lock
1	Open-frame transformer
1	Set of battery leads
1	Hardware pack
1	Literature – Installation Guide

Technical specifications

Mechanical Properties

Dimensions:	15.5 in. high x 12 in. wide x 4.5 in. deep (39.4 cm high x 30.5 cm wide x 11.4 cm deep)
Weight:	17 lbs (7.7 kg)

Trademarks

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

Ordering information

AL802-WAL NAC Power Extender (8 A)

8 A remote power supply/battery charger that can be connected to any 12 VDC or 24 VDC FACP
Order number **AL802-WAL**

Accessories

AL800LGK9E Logic Board

Replacement board used with the AL802-WAL or AL1002WAL NAC Power Extenders; mounts in enclosure
Order number **AL800LGK9E**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
203 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com