

Product data sheet

Specifications



APC Step-Down Transformer RM 2U 208V IN 120V OUT; w/5-20 Receptacles

AP9626

Overview

Presentation	The Step-Down Transformer converts high voltage (208 or 200 VAC) output into low voltage (120 or 100 VAC) output for powering low voltage AC equipment.
Lead time	Usually in Stock

Main

Main Input Voltage	208 V
Main Output Voltage	120 V
Input Connection Type	NEMA L6-30P
Number of rack unit	2U
Number of cables	1
Provided Equipment	User Manual Rack Mounting brackets

Physical

Color	Black
Height	3.50 in (8.9 cm)
Width	17.52 in (44.5 cm)
Depth	24.02 in (61 cm)
Net Weight	95.20 lb(US) (43.18 kg)
Mounting Location	Front
Mounting preference	No preference
Mounting Mode	Rack-mounted

Input

Acceptable Input Voltage	208 V
Max line current	24 A
Input current limits	30 A
Load Capacity	5000 VA

Output

Maximum Total Current Draw per Phase	24 A
--------------------------------------	------

Number of power socket outlets	12
Efficiency	90 %
Number of power socket outlets	12 NEMA 5-20R

Conformance

Product Certifications	CSA
Standards	OSHDP UL 1778

Environmental

Ambient Air Temperature for Operation	32...104 °F (0...40 °C)
Relative Humidity	0...95 %
Operating altitude	0...10000 ft
Ambient Air Temperature for Storage	5...113 °F (-15...45 °C)
Storage Relative Humidity	0...95 %
Storage altitude	0...50000 ft (0.00...15240.00 m)

Ordering and shipping details

GTIN	731304249139
------	--------------

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	10.00 in (25.4 cm)
Package 1 Width	37.52 in (95.3 cm)
Package 1 Length	24.49 in (62.2 cm)
Package 1 Weight	110.23 lb(US) (50 kg)

Offer Sustainability

REACH Regulation	REACH Declaration
EU RoHS Directive	Compliant EU RoHS Declaration
Lead free	Yes
Mercury free	Yes
RoHS exemption information	Yes
Optimized Energy Efficiency	Energy efficient product
Take-back	Take-back program available

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------

Recommended replacement(s)